

Ham_Radio_Basic_Notes_1999.txt

Novice:

power	meters	Frequency	CW	RTTY	DATA	SSBphone
200	80	3.675-3.725	X			
200	40	7.1-7.15	X			
200	15	21.1-21.2	X			
200	10	28.1-28.3	X	X	X	
200	10	28.3-28.5	X			X
25	1.25	222.0-225.0	X	X	X	X
5	.23	1270-1295	X	X	X	X

.5 wave dipole = $468/f$ (ft)

.25 wave = $234/f$ (ft)

wave length (meters) = $300/f$

f = MHz

CW - Send CQ(calling) 3 times DE (from), your call 3 times

CW - Answer other call (signs) twice, DE, Your call twice.

RST - Readability, strength, tone

QRS - Slowly

QTH - Location

QSL - written acknowledgment postcard

Voice - Send CQ 3 times, this is, your call 3 times

Voice - Answer CQ other call twice, this is, your call twice

QRL - CW to see if frequency in use send QRL?

QSY - change frequency

QSO - Conversation in progress

QRZ - CW is some one calling me? send QRZ?

voice use phonetics for your call sign

RTTY - CQ 3-6 times, DE, your call 3 times